

---

## Guarding Expert Instructions

- Download Guarding Expert
- On the top left of app there are 3 bars, select to open Menu
- Select the third icon, **Devices** (blue icon)
- Select the plus (+) sign in top right corner, choose Manual Adding
- **For setup using a DDNS Name follow below:**
  - **Alias:** Nickname or what you want to call the DVR/NVR, i.e. HOME
  - **Register Mode:** HiDDNS
  - **Device Domain:** is the DDNS name you made at DVR/NVR, i.e. 123amityst
  - **User Name:** the user name needed to access DVR/NVR
  - **Password:** the password needed to access the DVR/NVR
  - **Camera No.:** By default this is at "1", once all the above info is added correctly and saved this number will automatically change to the amount of cameras connected to the DVR/NVR.
- Hit the **Save** button in the top right hand corner
- Hit **"Start Live View"** down at the bottom of the screen
- **For setup using a Static WAN IP Address follow below:**
  - **Alias:** Nickname or what you want to call the DVR/NVR, i.e. HOME
  - **Register Mode:** IP Domain
  - **Address:** Static WAN IP address entered here, must be **STATIC** (will not change)
  - **Port:** Server Address Port that was opened in DVR/NVR
  - **User Name:** the user name needed to access DVR/NVR
  - **Password:** the password needed to access the DVR/NVR
  - **Camera No.:** By default this is at "1", once all the above info is added correctly and saved this number will automatically change to the amount of cameras connected to the DVR/NVR.
- Hit the **Save** button in the top right hand corner
- Hit **"Start Live View"** down at the bottom of the screen